

MODELS YRB67-1, YRB67-2,
YRB82-1

GENERAL ELECTRIC CO. PARTS DESCRIPTION LIST

MODELS YRB 82-1, YRB 67-1, YRB 67-2

Symbol	Description	Symbol	Description	Symbol	Description
C1	Ant. trimmer condenser	C14	.05 mfd paper capacitor	R2	2.2 megohm carbon resistor
C2A	Tuning condenser, ant. section	C15	.05 mfd paper capacitor	R3	Volume control .5 megohm
C2B	Tuning condenser, osc. section	C16	.05 mfd paper capacitor	R4	4.7 megohm carbon resistor
C3	Osc. trimmer condenser	C17	.01 mfd paper capacitor	R5	470,000 ohm carbon resistor
C8	220 mmfd mica capacitor	L1	1st I.F. transformer	R6	470,000 ohm carbon resistor
C9	.005 mfd paper capacitor	L2	2nd I.F. transformer	R7	150 ohm carbon resistor
C10	220 mmfd mica capacitor	L3	Loop assembly	R8	2700 ohm carbon resistor
C11	.01 mfd paper capacitor	L4	Oscillator coil	R9	18 ohm carbon resistor
C12	.02 mfd paper capacitor	P1	Pilot lamp	R10	470 ohm carbon resistor
C13A	30 mfd electrolytic capacitor	T1	Output transformer		
C13B	30 mfd electrolytic capacitor	R1	22,000 ohm carbon resistor		

REPLACEMENT PARTS LIST

MODELS YRB 82-1, YRB 67-1, YRB 67-2

Stock No.	Description	Stock No.	Description
SPECIALIZED G-E REPLACEMENT PARTS		SPECIALIZED G-E REPLACEMENT PARTS (Cont.)	
SAB 004	Back cover, Models YRB 67-1 and 67-2	STL 001	Transformer, 1st I.F.
SAB 006	Back cover, Model YRB 82-1	STL 002	Transformer, 2nd I.F.
SAC 001	Cabinet, Model YRB 82-1	STO 001	Transformer, output
SAY 003	Cabinet, Model YRB 67-1	SWL 001	Power cord
SAY 015	Cabinet, Model YRB 67-2		
SCE 002	Capacitor, filter electrolytic, 30-30 mfd 150 volt, C13A, C13B	UNIVERSAL G-E REPLACEMENT PARTS	
SCT 002	Capacitor, tuning, C2A, C2B	UCC 039	Capacitor, .005 mfd paper, C9
SDC 001	Cord, dial drive cord	UCC 040	Capacitor, .01 mfd paper, C17
SDK 002	Knob, Models YRB 67-1 and 67-2	UCC 041	Capacitor, .02 mfd paper, C12
SDK 010	Knob, Model YRB 82-1	UCC 045	Capacitor, .05 mfd paper, C14, C15, C16
SDP 001	Printer, dial scale	UCU 1036	Capacitor, 220 mmfd mica, C8, C10
SDS 004	Dial scale, Models YRB 67-1 and 67-2	UDL 013	Pilot lamp, Mazda 51
SDS 006	Dial scale, Model YRB 82-1	UOP 526	Speaker, 5 1/4 inch PM dynamic
SHC 001	Hair pin cotter for dial drive	URD 007	Resistor, 18 ohm 1/2 watt carbon, R9
SJP 002	Connector, female to speaker	URD 029	Resistor, 150 ohm 1/2 watt carbon, R7
SJS 001	Pilot lamp socket	URD 041	Resistor, 470 ohm 1/2 watt carbon, R10
SJS 093	Socket, octal tube	URD 081	Resistor, 22,000 ohm 1/2 watt carbon, R1
SIC 001	Coil, oscillator	URD 113	Resistor, 470,000 ohm 1/2 watt carbon, R5, R6
SLI 001	Loop, antenna	URD 129	Resistor, 2.2 megohm 1/2 watt carbon, R2
SMF 002	Snap button	URD 137	Resistor, 4.7 megohm 1/2 watt carbon, R4
SMF 003	Fastener, back cover to cabinet	URE 059	Resistor, 2700 ohm 1 watt carbon, R8
SMS 001	Spring, dial drive drum		
SMU 001	Shaft, dial drive		
SMW 001	Pulley, dial drive		
SRC 003	Volume control, 0.5 megohm with power switch		